

# Maintenance Guidelines

## General

- Check if product works correctly.
- Check all bolts and nuts, tighten if needed.
- Check device for stability.
- Check safety of the surface.
- Register all inspections and maintenance.

## Fasteners

at least 2x a year

- Fasteners like bolts, nuts, washers etc. must be replaced immediately when damaged or worn.

## Bearings/gears/springs/drive belts

at least 2x a year

- Check gears. Take away backlash if needed.
- Grease bearings/gears with suitable grease.
- Check springs and drivebelts on deformation and damage. Replace when damaged or worn.

## Chains

at least 4x a year

- Check chains for damage between links.
- When a link has worn for over 30%, replace immediately.

## Wood

at least 6x a year

- Inspect regularly for cracks, tears, splinters and burn marks.
- Damaged spots need to be scraped out and dried.
- Retouch the spots, sand them and repaint.

## Plastics/rubbers/moulded resins

at least 2x a year

- Clean with water or an environmental friendly cleaning detergent.
- Check for damaged or worn patches. Retouch when possible or replace.

## Steel

at least 2x a year

- Clean with water or an environmental friendly cleaning detergent.
- Cracks and rusted steel need to be repaired immediately.
- Touch up light scratches and corrosion.

## Electrical components

at least 2x a year

- Check if Human Power supply (generator) runs smoothly.
- Listen to the speaker sound quality.
- Check the LED-strips for failures.
- Check functionality of buttons.
- Check cables for damages. Replace or fix when damaged.
- Check plugs for moist and welds. Replace or fix when damaged.
- Check if the USB-port is covered against moist.
- Check functionality of the disinfection pump.
- Update your timelock. Check the User Manual for the instructions.
- Do not worry about moisture between moulded PCB's and PC covers.

## Product Specific Maintenance

- AudioSense: replace smell cartridge 4x a year.
- AudioBench: Check stop-block on cracks and damage 3x a year.
- ProtectoNetic: Clean nozzle, filters and reservoir 3x a year.

## User Manuals

Use our products according to the Playnetic User Manuals. For subjects like volume, content and timelock, follow the instructions in these manuals.

## Installation Manuals

Install our products according to the Playnetic Installation Manuals.

Collect your manuals at:  
[www.playnetic.nl/products/](http://www.playnetic.nl/products/)



**playNETIC**  
Human Powered Play